








## Base Camp Distribution

	<b>Model No:</b>	<b>CFT600-CS3</b>
	Description	600 Amp Camlock Flow-Thru to "California Style" 50a Twistlock Distro
	Phase & Amperage (line/total)	3-phase 200a / 600a
	Input Type - Flow Thru	3-phase 400a 208Y-/120v Camlock Type
	Output Type	6-50a 125/250v Twistlock, 1-20a Courtesy, & Voltage Test Jacks
	Circuit Protection	6-50a 240v & 1-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	19.5"L x 12.5"W x 11.5"H - 37lbs.
	<b>Model No:</b>	<b>CFT600-CS</b>
	Description	600 Amp Camlock Flow-Thru to "California Style" 50a Twistlock Distro
	Phase & Amperage (line/total)	1-phase 300a / 600a
	Input Type - Flow Thru	1-phase 400a 120v/240v Camlock Type
	Output Type	6-50a 125/250v Twistlock, 1-20a Courtesy, & Voltage Test Jacks
	Circuit Protection	6-50a 240v & 1-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	19.5"L x 12.5"W x 11.5"H - 36lbs.
	<b>Model No:</b>	<b>TLB100-E30RV</b>
	Description	50a Twistlock Flow-Thru to RV & Edison Lunchbox
	Phase & Amperage (line/total)	1-phase 50a / 100a
	Input Type - Flow Thru	50a 125/250v Twistlock
	Output Type	2-30a 125v RV & 2-20a 125v Edison Duplex Recept.
	Circuit Protection	2-30a 120v & 2-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	9.5"L x 8"W x 8.5"H - 9lbs.
	<b>Model No:</b>	<b>TLB80</b>
	Description	50a Twistlock Flow-Thru to Edison Lunchbox
	Phase & Amperage (line/total)	1-phase 40a / 80a
	Input Type - Flow Thru	50a 125/250v Twistlock
	Output Type	4-20a 125v Edison Duplex Recept.
	Circuit Protection	4-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	9.5"L x 8"W x 8.5"H - 9lbs.
	<b>Model No:</b>	<b>LB100-E30RV</b>
	Description	100 Amp Stage Pin Flow-Thru to RV & Edison Lunchbox
	Phase & Amperage	1-phase 100 Amp Max.
	Input Type - Flow Thru	100a 125v Stage Pin
	Output Type	2-30a 125v RV & 2-20a 125v Edison Duplex Recept.
	Circuit Protection	2-30a 120v & 2-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	9.5"L x 8"W x 8.5"H - 9lbs.
	<b>Model No:</b>	<b>LB90-30RV</b>
	Description	100 Amp Stage Pin Flow-Thru to RV Lunchbox
	Phase & Amperage	1-phase 90 Amp Max.
	Input Type - Flow Thru	100a 125v Stage Pin
	Output Type	3-30a 125v RV Recept.
	Circuit Protection	3-30a 120v Circuit Breakers (10K AIC)
	Dimensions & Weight	9.5"L x 8"W x 8.5"H - 9lbs.

Base Camp Distribution Pg. 2

	<b>Model No:</b>	<b>CFRV390</b>
	Description	390 Amp Camlock Flow-Thru to 30amp & 50amp RV Distro
	Phase & Amperage (line/total)	3-phase 130a / 390a
	Input Type - Flow Thru	3-phase 400a 208Y-/120v Camlock Type
	Output Type	3-30a 125v RV, 3-50a 125/250v RV, 2-20a Courtesy, & Test Jacks
	Circuit Protection	3-30a 120v, 3-50a 240v, & 2-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	19.5"L x 12.5"W x 11.5"H - 32lbs.
	<b>Model No:</b>	<b>CFRV420</b>
	Description	420 Amp Camlock Flow-Thru to 30amp & 50amp RV Distro
	Phase & Amperage (line/total)	1-phase 210a / 420a
	Input Type - Flow Thru	1-phase 400a 120v/240v Camlock Type
	Output Type	4-30a 125v RV, 3-50a 125/250v RV, 1-20a Courtesy, & Test Jacks
	Circuit Protection	4-30a 120v, 3-50a 240v, & 1-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	19.5"L x 12.5"W x 11.5"H - 30lbs.
	<b>Model No:</b>	<b>CFRV600-503</b>
	Description	600 Amp Camlock Flow-Thru to 50amp RV
	Phase & Amperage (line/total)	3-phase 200a / 600a
	Input Type - Flow Thru	3-phase 400a 208Y-/120v Camlock Type
	Output Type	6-50a 125/250v RV, 1-20a Courtesy, & Voltage Test Jacks
	Circuit Protection	6-50a 240v & 1-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	19.5"L x 12.5"W x 11.5"H - 32lbs.
	<b>Model No:</b>	<b>CFRV600-50</b>
	Description	600 Amp Camlock Flow-Thru to 50amp RV
	Phase & Amperage (line/total)	1-phase 300a / 600a
	Input Type - Flow Thru	1-phase 400a 120v/240v Camlock Type
	Output Type	6-50a 125/250v RV, 1-20a Courtesy, & Voltage Test Jacks
	Circuit Protection	6-50a 240v & 1-20a 120v Circuit Breakers (10k AIC)
	Dimensions & Weight	19.5"L x 12.5"W x 11.5"H - 30lbs.

Specifications subject to change

LIT-SST-BC-090104 © AC Power Distribution, Inc.

Additional models with Twistlock & Stage Pin outputs can be found in the "Twistlock" & "Stage Pin" categories.



**AC Power Distribution, Inc.....The Entertainment Industry's Power Solution!**



3060 N. California St. - Burbank, CA 91504  
 Tel: 818-848-4004 Fax: 818-848-4441 Toll Free: 877-55-ACPWR  
[www.acpowerdistribution.com](http://www.acpowerdistribution.com)